

emp^{ress}
effects

Reverb



User Manual

Firmware Version 6.41

Further Information

On our website (www.empresseffects.com) you will find lots of further information and details on the following points:

Download

This manual is also available as a PDF file for you to download.

Keyword Search

Use the search function in the electronic version of this manual to find your topics of interest quickly.

Customer Support

If you have any problems with the device our Customer Support team will gladly assist you.

Symbols and Signal Words

Signal Word	Meaning
DANGER!	This combination of symbol and signal word indicates an immediate dangerous situation that will result in death or serious injury if it is not avoided
CAUTION!	This combination of symbol and signal word indicates a possible dangerous situation that can result in minor injury if it is not avoided.
NOTICE!	This combination of symbol and signal word indicates a possible dangerous situation that can result in material and environmental damage if it is not avoided.

Warning Signs	Type of Danger
	General warning sign
	Electricity Hazard
	Hot Surface
	Sudden Loud Noises

Intended Use

This pedal is designed for enhancing guitar tones in live performances and studio recordings. Use as outlined in the user manual.
The manufacturer is not liable for damages resulting from improper use or use under non-recommended conditions.

Safety

	DANGER! Danger for children Dispose of plastic bags and packaging properly to keep them out of reach of babies and young children to prevent choking hazards. Ensure children don't detach small parts like knobs to avoid choking. Never leave children unattended with electrical devices.
	DANGER! Electrical shock Risk of electrical shock from exposed wires or damaged components. Inspect pedals for damage before use. If damaged, stop use and seek professional repair.
	DANGER! Power Supply Issues Use the right voltage and current for your pedal's power supply to prevent damage and safety risks. Check the power supply's condition, and for multiple pedals, opt for a dedicated supply to avoid overloading by daisy-chaining.
	CAUTION! Overheating Avoid overheating. Do not stack pedals or place in confined spaces. If a pedal overheats, stop using and let it cool.
	CAUTION! Tripping Hazard / Pedal Placement Prevent tripping: Secure cables and place pedals firmly to avoid slips and falls.
	CAUTION! Volume Spikes Beware of volume spikes and unexpected sounds when adjusting pedal settings
	NOTICE! Allergies or Sensitivities Allergy Alert: Some pedal materials, like adhesives and coatings, may cause reactions. Stop use and seek medical advice if needed.
	NOTICE! Fire Hazard Keep away from direct heat and open flames.

Contents

Introduction.....	vi
Quickstart.....	1
Mode Reference Chart.....	3
Firmware Updates	7
Presets	8
Controls at a Glance	12
V30 Looper.....	14
Control Port.....	16
MIDI Control Change Messages Reference	20
Powering The Reverb.....	22
Advanced Configuration	22
Advanced Configuration Reference.....	24
Factory Reset	26
Regulatory Compliance Information	26
Thank You.....	28
Specifications.....	31

Introduction

We're stoked you've chosen to make the Empress Reverb part of your sound! We've worked really hard to provide beautiful realistic studio-quality reverbs, as well as many creative new modes. You'll soon discover the tone palette is deep and diverse.

It was important for us to create a pedal that's tweakable but fast to dial in. We wanted all the functions at your finger tips and accessible with your toes. The many advanced configuration options let you customize the pedal to meet your needs, so be sure to check those out.

If any section of this manual is unclear, check our tutorial videos online - sometimes a moving picture with sound is worth a million words.

Also, the pedal can be updated via the SD card slot, so make sure to check empresseffects.com often for the latest firmware.

Now go make some music!



Steve Bragg - Designer

Quickstart

All modes are designed to sound good with all knobs at 12 o'clock. Start there and then tweak to taste.

Concert Hall

● sparkle

● modulation

● ambient swell

● delay + reverb

● reverse

● ghost

● lo-fi

● beer

● hall

● plate

● spring

● room

● decay

● mix

● output

● low

● hi

● thing 1

● thing 2

Modulated

● sparkle

● modulation

● ambient swell

● delay + reverb

● reverse

● ghost

● lo-fi

● beer

● hall

● plate

● spring

● room

● decay

● mix

● output

● low

● hi

● thing 1

● thing 2

Ghost

● sparkle

● modulation

● ambient swell

● delay + reverb

● reverse

● ghost

● lo-fi

● beer

● hall

● plate

● spring

● room

● decay

● mix

● output

● low

● hi

● thing 1

● thing 2

Room

● sparkle

● modulation

● ambient swell

● delay + reverb

● reverse

● ghost

● lo-fi

● beer

● hall

● plate

● spring

● room

● decay

● mix

● output

● low

● hi

● thing 1

● thing 2

Delay + Reverb

● sparkle

● modulation

● ambient swell

● delay + reverb

● reverse

● ghost

● lo-fi

● beer

● hall

● plate

● spring

● room

● decay

● mix

● output

● low

● hi

● thing 1

● thing 2

Reverse

● sparkle

● modulation

● ambient swell

● delay + reverb

● reverse

● ghost

● lo-fi

● beer

● hall

● plate

● spring

● room

● decay

● mix

● output

● low

● hi

● thing 1

● thing 2

Mode Reference Chart

Mode	Description	Thing 1	Thing 2
Hall			
🔵 Concert Hall	Classic large hall sound, very warm, slow build, with long smooth decay.	Modulation	Early Reflection Level
🟢 Modern Hall	Hall that's very smooth and warm without any modulation.	Pre-Delay Time	Early Reflection Level
Plate			
🔵 Classic Plate	Modeled after a vintage plate, works at both short and long decays.	Pre-Delay Time	Bright Early Decay
🟢 Studio Plate	Very smooth decay, no modulation.	Pre-Delay Time	Early Reflection Level
Spring			
🔵 Bright Spring	In the Fender Twin Reverb realm.	Rattle Decay	Rattle Level
🟢 Dark Spring	In the Fender Deluxe realm.	Rattle Decay	Rattle Level
🔴 Overdriven Spring	Dirty 60's Surf Sound.	Rattle Decay and Level	Break-up amount
🟡 Drip Spring	Lush and swirly spring reverb.	Rattle Decay	Rattle Level
🔵 Spring + Trem	Amp-like tremolo, applied after the Drip Spring.	Tremolo Rate	Tremolo Depth
Room			
🔵 L.A. Studio	Very Realistic room with dense early reflections. Great at short decays.	Pre-Delay Time	Early Reflection Level

Sparkle

🔵 Sparkle	Adds smooth octaves and long decays.	Sparkle Level	Sparkle Length
🟢 Glummer	Octave down and up.	Octave down blend	Octave up amount

Modulation

🔵 Modulated	Very smooth and adds lots of thickness, width and airiness to the sound.	Modulation Rate	Modulation Depth
🟢 Chorused Reverb	Similar to <i>Modulated</i> but a more muted sound in the mid range frequencies.	Modulation Rate	Modulation Depth
🔴 Flanged Reverb	Has a wide-sweeping flanger type effect on the output.	Modulation Rate	Modulation Depth
🟡 Tremolo Reverb	Tremolo is applied after a smooth hall reverb.	Tremolo Rate	Tremolo Depth

Ambient Swell

🔵 Triggered Swell	Detects pick attacks and fades in the notes, eliminating attack in the reverb line.	Swell Time	Modulation
🟢 Gate Swell with Octave	A gate that then feeds a dense set of delays with octave. It will fade in to create smooth swells.	Gate Attack	Octave Up volume
🔴 Freezification	The select stomp provides a freezification of the sound.	Transition Speed	Frozen Sound Level
🟡 Seed	The sweet sound of a growing tail with lots of modulation, and width that opens as it decays.	Diffusion	Size

Delay+Reverb

Single Tap Delay	Adds a delay to the warm hall setting, very cool for lead parts.	Delay Time	Delay Feedback
Blend-able Delay	Delay time is set with select stompswitch.	Blend of reverb vs delay	Delay Feedback
Filtered Feedback Delay	The Hi and Low knobs filter the delay feedback.	Delay Time	Delay Feedback
Skitter	Delays that morph into reverb.	Diffusion	Size

Reverse

Reverse with Decay	Reverse Reverb with a nice smooth decay.	Reverse Swell Time	Reverse Modulation
Reverse and Stop	Reverse Reverb with no decay.	Pre-Delay	Diffusion
Reversed Delay	Reverse Delay with ability to add Reverb.	Reverse Delay Length	Amount of Reverb added to the reverse delay

Ghost

Resonant	It's a spooky sounding decay because of aggressive resonances in the response.	Mod Rate	Resonance (aka spookiness)
Casper	A Friendlier, less spooky ghost.	Modulation	Diffusion

Lo-Fi (filter applied to wet and dry signals)

50's Radio	Grainy, filtered lo-fi sound with an AM radio quality to it.	Delay Level	Dirtiness
Warble	Distorted and wobbly delay lo-fi sounds.	Warble	Dirtiness

Beer

Glitch	The reverb tail is fed into a filter that randomly changes between low-pass and high-pass.	Glitch Speed	Glitch Tone - determines the time spent on HPF vs. LPF
Gated Reverb	When you stop playing, a gate mutes the wet signal.	Gate Threshold	Gate Release (10ms - 1sec)
Destroyer Pad	For sternly communicating with household appliances.	Robot screams	Pitch shift



This manual only lists modes that were available at the time of printing. For the most up-to-date firmware and manual refer to empresseffects.com

Firmware Updates

This pedal has firmware that can be updated with an SD card.

Performing A Firmware Update

1. Download the firmware file off the website (empresseffects.com/reverb-firmware)
2. Copy the file to the root directory of the SD card (a high-capacity SD card that's been formatted FAT32)
3. Insert the SD card then power on the pedal.
4. The preset LEDs should marquee yellow for a bit, then all turn green when the update is complete.
5. Remove the SD card, cycle the pedal's power, and you're good to go!

SD Card Constraints

There should only be one partition on the SD card because the pedal only looks at the first partition on the disk. SD card must be V2 high speed. Nowadays this is the most common type.

Firmware Update Error Codes

The preset LEDs will blink to signal an error:

1. Unusable card
2. V1 card
3. V2 standard card
4. Unable to read disk
5. Valid FAT volume not found on SD card.

Presets

The Reverb has two types of preset systems: the **scrolling preset system**, and the **bank preset system**. Read about each preset system to find which one will work best for you. Select which preset system to use in *Advanced Configuration*.

SCROLLING PRESET SYSTEM

Preset Organization

In *Advanced Configuration* you can select the number of presets you wish to use. The presets are represented by a series of 5 LEDs located just below the knobs. Press the **scroll** stompswitch to scroll through the presets. The preset LEDs will blink. When cycling through the presets after every 5 presets, the preset LED colors will change to another color to indicate you're in the next bank and will start counting again from left to right.

When cycling through the presets you will notice that after your final preset, all the preset LEDs will flash very quickly. This represents the manual preset. If you recall this preset, the Reverb will get its settings from the current knob positions. In the manual preset, no preset LEDs are lit.

You can scroll backwards through the presets by pressing the **select** and **scroll** stompswitches simultaneously.

Saving a Preset

To save the current settings to a preset, press the **scroll** stompswitch until you reach the preset location you want to write to. While the lights are flashing, hold down the **save** button and press the **scroll** stompswitch. Your preset is now saved.

Recalling a Preset

To recall a preset simply press the **scroll** stompswitch until the preset you'd like to recall is flashing, then press the **select** stompswitch to load the preset. The presets LEDs should now be solid and bright.

Changing a Preset

If you change the position of a knob or switch after a preset is loaded, the preset LEDs will dim to indicate that the preset has been modified, but not saved. If you move the knob or switch back to the position it was in when the preset was saved, the preset's LED indicators will brighten again. This lets you find the positions of all the knobs and switches when the preset was saved.

Preset Organization

In *Advanced Configuration* you'll select the number of banks you wish to use. The preset LEDs display which bank is selected by changing color. Each stompswitch represents a preset. So there are 3 presets per bank.

Recalling a Preset and Bypassing the Pedal

To recall a preset, press on a stompswitch. The light above that stompswitch and the bypass LED will illuminate. To load another preset, simply press one of the other stompswitches. To bypass the pedal, press the stompswitch corresponding to the active preset, and the bypass LED will turn off. The pedal is now bypassed.

Changing Banks

To bank up, press the right and middle stompswitches simultaneously. To bank down press the left and middle stompswitches simultaneously. The LEDs will flash indicating the target bank, then you can press any of the stompswitches to load a preset within that bank.

Saving a Preset

To save a preset, set the knobs to the sound you would like to save. Then navigate to the target bank. While the lights are blinking, press and hold the **save** button and select the target preset location by pressing the corresponding stompswitch.

SAVING/LOADING PRESETS TO/FROM SD CARD

To save presets to an SD card, make a folder in the root directory of the SD card called "from_reverb". On startup, the Reverb will populate this directory with all the current presets and the advanced configuration settings.

To load presets from an SD card, make a folder in the root directory of the SD card called "to_reverb". Presets that are named "xx_reverb.bin", where "xx" is a number between 0 and 35 inclusive, will be loaded into the corresponding preset slots.

The SD card must be formatted as FAT32 with the largest allocation unit size (64 KB for most 16 GB cards).

Controls at a Glance

decay: controls how long the reverb tail takes to decay.

mix: sets the ratio of wet signal (reverb) to dry signal (unaffected). Counterclockwise is 100% dry, clockwise is 100% wet, with 50/50 being somewhere around 2 o'clock.

output: controls the overall output volume for the pedal. 12 o'clock is unity.

thing 1 & thing 2: these two controls take on different functions depending on the mode. They control things like modulation, early reflections, pre-delay, sparkle, octave level, delay time and feedback. Check the mode reference chart to see which function they perform in a given mode.

bypass: engage or bypass the pedal. Can be set for true bypass or buffered bypass in advanced configuration.

select + scroll together: will scroll backwards through presets.

scroll: press to scroll through presets, then engage the preset with the select switch.

select: used to engage a preset that has been scrolled to with the scroll footswitch. Also used as a tap switch or infinite hold when not scrolling through presets.

To Save a Preset:

- create the sound you want to save
- scroll to the preset location you would like to save to
- press and hold the **save** button
- press the **scroll** footswitch
- release **save** and **scroll**

To Assign Expression Pedal:

- move knob(s) to desired setting(s) for heel position
- press and hold **save** button
- move knobs to desired setting(s) for toe position
- release **save** button

mode selector: selects which mode is active. Each mode can have many submodes which are indicated by different color LEDs.

low and hi: controls the reverb tone through EQ and damping.

presets: a row of five indicator lights below the main knobs.

Reverb
empress

V30 Looper

The Reverb contains a multitrack looper which can record loops up to 10 minutes. The looper is available in firmware version 5.03 and up. The latest firmware can be found on our website at www.empresseffects.com/reverb-firmware



The looper requires an SD card that says V30 on it. Numbers larger than V30 (V60, V90, etc) are okay too.

An SD card with minimum 4GB of storage must be inserted into the Reverb to operate the looper.



WARNING! The V30 looper will corrupt any data on the SD card, so don't use a card with important stuff on it!

ENABLING THE LOOPER

To enable the looper, enter Advanced Configuration (see *Advanced Configuration*). Turn the **mode** knob until the Plate Green LED is lit, then turn the **decay** knob clockwise until the second preset LED is lit. The looper will be enabled upon exiting Advanced Configuration.

Effects Routing (making looper pre- or post-effect)

While still in Advanced Configuration, turn the **mode** knob until the Spring Green LED is lit, and then turn the **decay** knob to select either looper pre (preset LED 1) or post (preset LED 2) effect. Exit Advanced Configuration to save your settings.

USING THE MULTITRACK LOOPER

Entering/Exiting Looper User Interface – press and hold middle and right stompswitches together for 1 second. Now, the stompswitches will control the looper as outlined below, and the preset leds will show the looper state. To exit the looper UI, hold middle and right stompswitches again for 1 second, and you can use the stompswitches to control the pedal as normal while the looper continues to play.

Move Active Track Right – press middle and right stompswitches together.

Move Active Track Left – press middle and left stompswitches together.

Start/Stop Recording – press left stompswitch

Play/Stop – press right stompswitch

Mute/Unmute Active Track – press middle stompswitch

Clear Active Track – press and hold middle and left stompswitches together for 1 second.

Clear All Tracks – move to an empty track and press and hold middle and left stompswitches together for 1 second.

Adjust Looper Playback Volume – adjust the **output** knob while the looper UI is active.

LOOPER LED COLORS

The state of any given track is represented by the color of its corresponding LED. The bright LED is the active track.

 Green	Track is currently playing
 Blue	Track is active but doesn't contain any audio
 Red	Track is currently recording
 Aqua	Track contains audio, but looper is stopped
 Yellow	Track is muted
 Purple	Track is recording but is muted

Additional Looper Notes:

While in looper UI mode, the knobs still affect the reverb sound, so you can change up the modes or the parameters while in the looper UI.

Any audio tracks that are playing will still play when you exit looper UI mode.

The looper will still play when the pedal is bypassed, unless you have the pedal set to true bypass.

Control Port

The control port jack allows the Empress Reverb to be controlled by a multitude of devices. The pedal ships configured to accept an expression pedal. Please see the *Advanced*

Configuration section on how to configure the control port for the device you plan to use.

EXPRESSION PEDAL

Each parameter, with the exception of the **mode** knob, can be controlled simultaneously via the expression pedal.

To control a parameter with the expression pedal, move the parameter's knob to the desired heel setting, then hold down the **save** button and move the knob to the desired toe setting, then release the **save** button. Multiple parameters can be assigned for expression pedal control simultaneously by repeating this process for each parameter to be assigned. Each parameter can be set with independent heel and toe settings.

To release a parameter from the expression pedal's control, move the knob that controls that parameter.

Any expression pedal used with the Empress Reverb should have the following pinout: tip to signal, ring to power, and sleeve to ground.

CONTROL VOLTAGE (CV)

With CV control, the Empress Reverb responds to CV signals from 0 to 5 volts. Otherwise, the CV configuration works exactly like the expression pedal configuration.

EXTERNAL TAP SWITCH

The Empress Reverb can be used with either a normally-open or a normally-closed external switch. This switch operates like the **select** stompswitch, with the exception of loading presets.

MIDI

All the parameters of the Reverb can be controlled via control change messages. Its presets can be selected with program change messages, and its tempo can be controlled with MIDI clock messages. The Reverb receives MIDI on the tip and transmits MIDI on the ring.

Before beginning, configure the pedal for MIDI control and set the MIDI channel. See *Advanced Configuration* for instructions. Choose a MIDI channel that won't conflict with other devices in your MIDI rig.

- To receive MIDI messages on your Reverb, you'll have to connect your MIDI device (or device with a MIDI type A TRS output) to the Reverb via a MIDI to TRS adapter (not included).
- To send and receive MIDI messages on your Reverb, you'll have to connect a MIDI device that supports receiving MIDI on the tip and transmitting MIDI on the ring, such as the Empress MIDIBox2 (not included).

Recalling a preset via MIDI (Program Change Messages)

You can activate a preset by sending a MIDI program change

message. For example, sending a program change message of 7 activates preset 7.

MIDI with Preset Out

The Reverb can send out MIDI program changes on the ring of the control port jack whenever a preset is loaded on the Reverb. The Reverb will send out these program changes on the 4 channels above the Reverb's current MIDI channel.

For example, if the Reverb is set to MIDI channel 5 and preset 3 is loaded, the Reverb will send out MIDI program change 3 on MIDI channels 6, 7, 8 & 9.

MIDI Beat Clock

Modes that accept a tap tempo input will respond to MIDI clock messages. MIDI clock specifies quarter notes, subdivided into 24 MIDI messages. The Reverb's delay time gets set to a quarter note.

MIDI Control Changes

The Empress Reverb can be controlled with MIDI control change messages. Opposite is a table that shows which MIDI control change number controls each Reverb parameter.

MIDI Control Change Messages Reference

Reverb Parameter	CC #:	Note:
Modes	20	The modes and sub-modes are numbered starting from 0 (Hall = 0, Plate = 1, etc.) To translate the modes and sub-mode to a single number you apply the following equation: MIDI message value = (mode x 8) + sub-mode <u>Example:</u> To load the 2nd plate mode, you'd send a value of 9 with the CC message. (1x8) + 1.
Recall Preset	11	Send preset # to recall that preset.
Decay Time	21	Sending a value 0 would be equivalent to the knob completely counterclockwise, sending 127 is equivalent to fully clockwise.
Mix	22	
Volume	23	
Low Damp	24	
Hi Damp	25	
Thing 1	26	
Thing 2	27	
Left Stompswitch - Select	35	Sending a value of 64 simulates a quick tap. Sending a value of 127 simulates the switch being pressed and held until a value of zero is sent, simulating releasing the switch.
Middle Stompswitch - Scroll	36	
Right Stompswitch - Bypass	37	
Save Button	38	

Save Preset	39	0-35 selects which preset the current settings get saved to. <i>In Bank mode the presets that appear are (1,3,5), (6,8,9), etc.</i>
Engage / Bypass	60	0 to bypass, 127 to engage.
Simulate Expression Pedal	10	0 to 127 as the sweep of the expression pedal from heel to toe.
MIDI Clock Listener	51	Sending a value of 0 causes the pedal to ignore MIDI clock messages. Sending a value of 127 causes the pedal to listen for MIDI clock messages. (by default, the pedal listens for MIDI clock)

Additional MIDI Control Change Notes

- MIDI switching cannot be done while in *Advanced Configuration*.
- The manual preset cannot be used while using the bank preset system.

Powering The Reverb

Go to www.empresseffects.com/power to learn if your power supply works for our pedals.

Please note: The Empress Reverb requires a minimum of 300mA to function properly. Any power supply rated at 9V DC with negative tip polarity and at least 300mA of current should work.

Advanced Configuration

The advanced configuration customizes how your pedal operates. The options are listed in the table that follows.

Entering Advanced Configuration

While holding down the **select** and **bypass** stompswitches, press the **save** button. All the preset LEDs will blink yellow twice to confirm you're in.

While in Advanced Configuration

Each mode LED represents a different configuration item you can change. Look up the item you'd like to change from the table on the right, then turn the **mode** rotary knob to select it.

Turn the **decay** knob to modify the value of the advanced configuration setting. The preset LEDs will illuminate to show you the current value. For example, if the hall mode light is lit and the 2nd preset LED is lit, you've configured the pedal for buffered bypass operation.

Exiting Advanced Configuration

Hold down **select** and **bypass** stompswitches while in advanced configuration. Preset LEDs will blink yellow twice and the pedal will reboot.

Advanced Configuration Reference

Option	Set mode LED to:	preset LEDs indicate:
Bypass operation	 Hall	1. True Hardwire Bypass 2. Buffered Bypass* 3. Buffered Bypass with isolation transformer on right output (Note: when transformer is engaged the pedal assumes stereo output operation)
Control port configuration	 Plate	1. Expression Pedal* 2. Control Voltage Input 3. Normally Open Switch 4. Normally Closed Switch 5. MIDI 6. MIDI with Preset Out
Input pad	 Spring	1. No Pad (0dB) 2. -6dB Pad* 3. -12dB Pad
Preset system	 Room	1. Scrolling Preset System* 2. Bank Preset System
Number of presets for scrolling preset system	 Sparkle	As you turn from left to right the LEDs will illuminate in order to indicate the last preset.
Number of banks for the bank preset system	 Modulation	As you turn from left to right the colors will indicate the last bank.
MIDI channel the pedal will respond to (when control port is configured for MIDI).	 Ambient Swell	As you turn from left to right the LEDs will illuminate in order to indicate the MIDI channel. (ex. If the 3rd LED is lit, it's going to listen on MIDI channel 3).

Knob Lock - lock the presets so they don't change accidentally on stage.	 Delay + Reverb	1. Unlocked* 2. Locked - knobs are locked in presets (not manual preset) 3. Total Lock – knobs locked and can't overwrite presets.
Cabinet Simulator puts a cabinet simulation algorithm on the output, useful if you don't have an amp.	 Reverse	1. Cab sim is off.* 2. Bright 4x12 cab. 3. Dark vintage cab 4. Balanced modern cab
Signal Configuration	 Ghost	1. stereo in/stereo out.* 2. wet/dry: dry out left, and wet out right. 3. Hardware insert - Pre 4. Hardware insert - Post
Startup State	 Lo-Fi	1. Startup Bypassed* 2. Startup Engaged and load Preset 1
Stereo Widening	 Beer	1. Regular Stereo Width* 2. Stereo Width 2dB wider. 3. Stereo Width 4dB wider.
Mix Knob Taper	 Hall	1. Wetter* 2. Dryer
Looper	 Plate	1. Disabled* 2. Enabled
Looper - Effects Routing	 Spring	1. Looper pre effect* 2. Looper post effect

***denotes the factory default setting**

Factory Reset



WARNING! This will overwrite your current presets and advanced config settings and replace them with the factory presets and default advanced config settings!

To restore the Reverb to its factory settings, do the following: while in the advanced configuration (see *Entering Advanced Configuration*): press and release the stompswitches in this order: **Select, Bypass, Select, Bypass**. Then the LEDs do a dance. Now you can exit advanced configuration (see *Exiting Advanced Configuration*).

Regulatory Compliance Information

ICES-003 (Canada)

CAN ICES-003(B) / NMB-003(B)

FCC (USA)

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:
(1) this device may not cause harmful interference, and
(2) this device must accept any interference received, including interference that may cause undesired operation.

Responsible Party in the USA

Americas Compliance Consulting LLC dba iCertifi

1001 SW Disk Drive, Ste 250

Bend, Oregon 97702 USA

FCC_sDoC@icertifi.com

icertifi.com

Changes or modifications not expressly approved by the party responsible for compliance could void the user's authority to operate the equipment.

Note: This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful

interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

CE (EU) and UKCA (UK)

This declaration of conformity is issued under the sole responsibility of Empress Effects Inc- 105-62 Steacie Dr, Kanata Ontario K2K 2A9. The device identified on the front page of this manual is in conformity with the requirements of:

- European Union: Electromagnetic Compatibility Directive 2014/30/EU
- United Kingdom: Electromagnetic Compatibility Regulations 2016 (SI 2016 No. 1091)

The following harmonized/designated standards have been applied:

- EN 55032:2015/A11:2020 – Electromagnetic compatibility of multimedia equipment - Emission Requirements
- EN 61000-3-2:2014 – Electromagnetic compatibility (EMC) - Part 3-2: Limits - Limits for harmonic current emissions (equipment input current ≤ 16 A per phase)
- EN 61000-3-3:2013 – Electromagnetic compatibility (EMC) - Part 3-3: Limits - Limitation of voltage changes, voltage fluctuations and flicker in public low-voltage supply systems, for equipment with rated current ≤ 16 A per phase and not subject to conditional connection
- EN 55035:2017/A11:2020 – Electromagnetic compatibility of multimedia equipment - Immunity Requirements



Colin King

Design Engineer
Empress Effects Inc
August 19, 2023

62 Steacie Dr, Suite 105, Kanata, Ontario K2K 2A9 Canada



WEEE (2012/19/EU)

This product must not be disposed of with regular household waste. In compliance with WEEE regulations, please take this product to a designated collection facility or return to the supplier for proper recycling. Comply with local laws and regulations for disposal. Contact your local authority or support@empresseffects.com for specific information.



Disposal of the packaging material

For the transport and protective packaging, environmentally friendly materials have been chosen that can be supplied to normal recycling. Ensure that plastic bags, packaging, etc. are properly disposed of. Do not just dispose of these materials with your normal household waste, but make sure that they are collected for recycling. Please follow the notes and markings on the packaging.



Thank You

Patrick Zdunich for lending his ear and super bug hunting skills when we needed it the most.

Steve Foley for giving us so much input on the functionality and his ears on the sounds.

Dave Bignell for making his studio available to a stranger for a day of listening.

Bova Sound for sampling their wonderful EMT 140 Plate Reverb. Young coding rock-star **Matt Cyr** for crushing it so hard on the calibration tools.

Chris 'C++' DeVisser for making us some awesome internal tools we use every day.

Thanks to beta testers **Dan Hay**, **Jordan Craig**, and **Jeff Logan** for their valuable input when we couldn't tell the forest from the trees.

Specifications

Input Impedance:	1M Ω
Left Output Impedance:	100 Ω
Right Output Impedance (transformer):	600 Ω
Frequency Response:	10Hz – 22kHz
Total Harmonic Distortion + Noise:	<0.1%
Input Headroom (dry):	+10.0 dBu
Input Headroom (wet, no pad):	+0.5 dBu
Output Headroom:	+16.2 dBu
Power Voltage:	9V DC Center-Negative
Power Input Connector:	2.1mm Barrel Connector
Required Current:	300mA
Height:	2.25"
Length:	5.7"
Width:	3.75"
Weight:	1.5 lbs